

Guide for Dimming VARILIGHT Dimmable DigiFlux EnergySaver+ Light Bulbs			
If you are planning to use this dimmer to control VARILIGHT Dimmable DigiFlux EnergySaver+ Light Bulbs, please refer to the table below to determine the minimum and maximum number you can dim.			
Type Of Dimmer	Dimmer Rating (As Shown On Rear Of Dimmer)	Number of VARILIGHT Dimmable DigiFlux EnergySaver+ Light Bulbs You Can Dim	
		1 Gang	2, 3 or 4 Gang (Per Gang)
VARILIGHT Standard Dimmer Switch	Min. 40W; Max. 250W	1 to 5	1 to 3 (or 2 to 5)*
	Min. 60W; Max. 400W	2 to 10	2 to 10
	Min. 60W; Max. 500W	2 to 15	N/A
VARILIGHT Intelligent Dimmer Switch	Min. 40W; Max. 300W	N/A	Not Suitable
	Min. 50W; Max. 400W	1 to 10	N/A
	Min. 50W; Max. 500W	1 to 10	N/A
VARILIGHT Touch or Remote Dimmer Switch	Min. 40W; Max. 250W	N/A	1 to 12
	Min. 40W; Max. 400W	1 to 15	1 to 15
	Min. 40W; Max. 600W	1 to 20	N/A
* For 2, 3 and 4 Gang 250W Standard Dimmers you must use between 1 and 3 Dimmable EnergySaver+ Light Bulbs on every gang of the dimmer, or between 2 and 5 Dimmable EnergySaver+ Light Bulbs on every gang of the dimmer. So, for example, you cannot use 5 on one gang of the dimmer and 1 on another but you can use 5 on one gang of the dimmer and 2 on another.			

APPLICATION ADVICE:

This product is not suitable for use with light-fittings where the light bulb is surrounded by a glass globe as over-heating may lead to early bulb failure.